

VX-260 SERIES

COMPACT, DEDICATED PTT COMMUNICATION

PORTABLE ANALOGUE RADIOS

For basic push-to-talk communication, look to the VX-260 Series.

Choose from two portable analogue radios: the VX-261 (without display) and VX-264 (with display). With enhanced interoperability, you can choose from multiple signalling options, such as: MDC1200®, FleetSync®, DTMF, and 2-tone or 5-tone capabilities for seamless integration into a mixed fleet. Available with a range of flexible energy solutions and accessories, you'll have all you need to provide your team with the perfect communication solution.

GENERAL FEATURES

- Channel Capacity:
 - 16 Channels/ 1 Group (VX-261)
 - 128 Channels/ 8 Groups (VX-264)
- Programmable Buttons:
 - 2 Programmable Buttons (VX-261)
 - 6 Programmable Buttons (VX-264)
- Display:
 - No Display (VX-261)
 - 8 Character Alphanumeric Display (VX-264)
- Safety Features:
 - Lone Worker Alert
 - Emergency Alert
- Multiple Scan Options
- Auto Range Transponding System (ARTS™)
- Voice Inversion Encryption (VX-264)
- Internal VOX (When Used with VOX Accessory)

SIGNALLING FEATURES

- CTCSS/DCS Encode and Decode
- MDC-1200® ANI Encode
- FleetSync® ANI Encode
- 2-Tone Encode/Decode
- 5-Tone Encode/Decode
- DTMF ANI Encode



GOODBYE
CROSSTALK



BROADEN
YOUR REACH



COME IN LOUD
AND CLEAR



KEEP YOUR
TEAM SAFE



POWER THROUGH
THE SHIFT



GENERAL SPECIFICATIONS

	VX-261	VX-264
Frequency Range	VHF: D0:136-174 MHz/UHF: G6:403-470 MHz	
Dimensions (H x W x D) with FNB-V133LI-UNI	109 x 58 x 32 mm (4.3 x 2.3 x 1.3 in)	
Weight	281 g (9.9 oz) (w/FNB-V133LI-UNI, Antenna, Belt Clip) 330 g (11.6 oz) (w/FNB-V134LI-UNI, Antenna, Belt Clip)	
Display	No	8 Character Alphanumeric
Power Output	5/1W	
Channel Spacing	25/20/12.5 kHz	
Audio Output	700 mW @ 16 Ohms (Internal)/500 mW @ 4 Ohms (External)	
Number of Channels	16	128
Number of Groups	1	8
Programmable Buttons	2	6
PC Programming Software	CE150	
Radio to Radio Cloning	Yes	
Battery Life	FNB-V133LI-UNI: 10.8 h (8.8 h w/o Saver)/FNB-V134LI-UNI: 19 h (15.5 h w/o Saver)	
IP Rating	IP55	
Power Supply Voltage	7.4 V DC (Nominal)	
Operating Temperature Range	-30° C to +60° C (-22° F to +140° F)	
Frequency Stability	±2.5 ppm	
RF Input-Output Impedance	SMA 50 Ohm	

RECEIVER SPECIFICATIONS measured by EN 300 086

Circuit Type	Double Conversion Superheterodyne
Sensitivity (20dB SINAD)	-2 dBµV Typical
Adjacent Channel Selectivity	65/60 dB (25 kHz/12.5 kHz)
Frequency	VHF: 136-174 MHz/UHF: 403-470 MHz
Channel Spacing	25/20/12.5 kHz
Intermodulation	65 dB
Spurious Image Rejection	70 dB
Hum and Noise	40 dB
Audio Output (5% THD)	700 mW @ 16 Ohms (Internal)/500 mW @ 4 Ohms (External)
Audio Distortion	< 5%
Conducted Spurious	-57 dB

TRANSMITTER SPECIFICATIONS measured by EN 300 086

Output Power	5/1 Watt
Modulation	16K0F3E / 14K0F3E / 11K0F3E
Maximum Deviation	±5.0 kHz / ±4.0 kHz / ±2.5 kHz
Conducted Spurious Emissions	70 dB Below Carrier
FM Hum and Noise	40 dB
Audio Distortion (@1 kHz)	< 5%

APPLICABLE MIL-STD

Standard	Methods/Procedures				
	MIL 810C	MIL 810D	MIL 810E	MIL 810F	MIL 810G
Low Pressure	500.1 proc 1	500.2 proc 2	500.3 proc 2	500.4 proc 1/2	500.5 proc 1/2
High Temperature	501.1 proc 1/2	501.2 proc 1/A1 proc 2/A1	501.3 proc 1/A1 proc 2/A1	501.4 proc 1/HOT proc 2/HOT	501.5 proc 1/A1 proc 2/A2
Low Temperature	502.1 proc 1	502.2 proc 1/Cat3 proc 2/Cat 1	502.3 proc 1/Cat 3 proc 2/Cat 1	502.4 proc 1/Cat 3 proc 2/Cat 1	502.5 proc 1/Cat 3 proc 2/Cat 1
Temperature Shock	503.1 proc 1	503.2 proc 1/A1 Cat 3	503.3 proc 1/A1 Cat 3	503.4 proc 1	502.5 proc 1/C
Solar Radiation	505.1 proc 2	505.2 proc 1	505.3 proc 1	505.4 proc 1	502.5 proc 1/A1
Rain	506.1 proc 1/2	506.2 proc 1/2	506.3 proc 1/2	506.4 proc 1/3	506.5 proc 1/3
Humidity	507.1 proc 2	507.2 proc 2	507.3 proc 2	507.4	507.5 proc 2/Agg
Salt Spray/Fog	509.1 proc 1	509.2 proc 1	509.3 proc 1	509.4	509.5
Blowing Dust	510.1 proc 1	510.2 proc 1	510.3 proc 1	510.4 proc 1	510.5 proc 1
Blowing Sand	-	510.2 proc 2	510.3 proc 2	510.4 proc 2	510.5 proc 2
Vibration	514.2 proc 8/FW	514.3 proc 1/Cat 10 proc 2/Cat 3	514.4 proc 1/Cat 10 proc 2/Cat 3	514.5 proc 1/Cat 24	514.6 proc 1/Cat 24
Shock	516.2 proc 1/2/3/5	516.3 proc 1/4/6	516.4 proc 1/4/6	516.5 proc 1/4/6	516.6 proc 1/4/6



Motorola Solutions Ltd. Nova South, 160 Victoria Street, London, SW1E 5LB, UK. www.motorolasolutions.com

Availability is subject to individual country law and regulations. All specifications shown are typical unless otherwise stated and are subject to change without notice.

MOTOROLA, MOTO, MOTOROLA SOLUTIONS and the Stylized M Logo are trademarks or registered trademarks of Motorola Trademark Holdings, LLC and are used under license. All other trademarks are the property of their respective owners. © 2017 Motorola Solutions, Inc. All rights reserved. 11-2017

ACCESSORIES

Antennas

- ATU-6A: 400-430 MHz 165 mm (6.5")
- ATU-6B: 420-450 MHz 155 mm (6.1")
- ATU-6C: 440-470 MHz 155 mm (6.1")
- ATV-6XL: Untuned VHF 178 mm (7")
- ATV-8A: 134-150 MHz 152 mm (6")
- ATV-8B: 150-163 MHz 152 mm (6")
- ATV-8C: 162-174 MHz 152 mm (6")

Battery

- FNB-V133LI-UNI: 1380 mAh Li-Ion
- FNB-V134LI-UNI: 2300 mAh Li-Ion
- FNB-V136-UNI: 1200 mAh Ni-MH

Carry Solutions

- LCC-261: Leather Case, Belt Loop (FNB-V133LI)
- LCC-261H: Leather Case, Belt Loop (FNB-V134LI)
- LCC-261S: Leather Case, Swivel Belt Loop (FNB-V133LI)
- LCC-261SH: Leather Case, Swivel Belt Loop (FNB-V134LI)
- LCC-264: Leather Case, Belt Loop (FNB-V133LI)
- LCC-264H: Leather Case, Belt Loop (FNB-V134LI)
- LCC-264S: Leather Case, Swivel Belt Loop (FNB-V133LI)
- LCC-264SH: Leather Case, Swivel Belt Loop (FNB-V134LI)
- CLIP-20: Belt Clip

Chargers

- CD-58: Charger Base
- PA-55C: AC Power Adapter for CD-58 (EU Plug)
- PA-55U AC Power Adapter for CD-58 (UK Plug)
- VAC-6058: MUC Charger
- VCM-5: Vehicular Charger Mounting Adaptor

Audio Accessories

- MH-360S: Compact Speaker Microphone with 3.5mm Audio Jack
- MH-450S: Speaker Microphone with 3.5mm Audio Jack
- MH-66A4B: IP57 Submersible Speaker Microphone
- MH-37A4B-1: Earpiece Microphone
- VH-150A: VOX Capable Lightweight Headset, Behind-the-Head
- VH-150B: VOX Capable Lightweight Headset, Over-the-Head
- MH-100: Rx Only Earpiece, 3.5mm for Use with MH-450S
- MH-101A4B: Single Wire Surveillance Kit
- MH-102A4B: 2-Wire Surveillance Kit



VX-261

VX-264



2A Klakotnitsa str. Sofia, Bulgaria
Telephone +359 2 9500 630
Web: www.komtek2006.com
Email: office@komtek2006.com